


SERVICE BULLETIN ML 0014



Date : 18 November 1999
Game : Slam'N'Jam
Subject : New Link Software

Distribution List

Asia : - MGF Operations, MGF Service
- LAI Asia Sales, Operations & Service

Installation Instructions :

This kit contains the new software for Linked Game Play for Slam'N'Jam. A single kit should contain the following Items

| Qty | Item Description |
|-----|--|
| 1 | 40Pin CPU AT89C52 Slam'N'Jam Link V2.2 |
| 1 | 27C64 EPROM Sound Program Link (SND PRG LNK) |
| 1 | 27C080 EPROM Sound Link 1 (SND LINK1) |
| 1 | 27C080 EPROM Sound Link 2 (SND LINK2) |
| 1 | 27C080 EPROM Sound Link 3 (SND LINK3) |
| 1 | 27C080 EPROM Sound Link 4 (SND LINK4) |
| 1 | Operators Manual |
| 1 | Assembly Manual |

1. Locate both the Game PCB and the Sound PCB (see page 34 of the Operators Manual)
2. Replace the 40Pin CPU at location IC2 on the Game PCB with the new Link V1.0 CPU. Be careful to insert the IC with the notch facing the fuses (See Photos)



3. On the Sound PCB replace all the EPROM's with the new Link Version. Note:- The Link Version uses two extra EPROM's. The locations are as follows

ROM0 = SND PRG LNK
ROM2 = SND LINK2
ROM1 = SND LINK1
ROM4 = SND LINK4
ROM3 = SND LINK5



4. Check and Adjust the Programming and Testing of the Link as explained in the Operators Manual.
5. Please return the Old CPU and EPROM's to your nearest LAI Games Distributor

Regards

LAI Games