

SERVICE BULLETIN ML 0003



Date : Friday, February 19, 1999
Game : Stop The Clock
Subject : Power fused on neutral line

Distribution List

Australasia : - LAI WA, SA, VIC, NSW & QLD - Sales, Operations, Service Departments
- LAI Games, NZ Coin Cascade, webmaster@lai.com.au
Asia : - ML Prod, ML Sales, MGF Operations, MGF Service, LAI Philippines
- LAI Asia Sales, Operations & Service

Problem : Power Distribution Box fused on neutral line

Solution : Remove DB box from machine and inspect for fuse in neutral line (See Figure 1). If this is the case follow the instructions listed below.

Parts Needed : 1 X 3mm crimp-ring
1 X 5mm Quick Connect terminal

1. Remove Blue wire from rear of fuse holder. Replace 5mm Quick Connect terminal on blue wire with 3mm-crimp ring (Save plastic insulation sleeve for step 4).
2. Remove Black wire from upper left terminal of double pole power switch (Going to front of fuse holder) and connect newly modified blue wire to this switch terminal.
3. Remove Brown wire from Lower right terminal of double pole power switch (going to line-in on noise filter) and connect the Black wire to this switch terminal.
4. Replace 3mm crimp ring on Brown wire with 5mm Quick Connect terminal and connect to the rear of fuse holder
5. Inspect that all new Joints are correct (See Figure 2) and reinstall DB box into machine

Figure 1 Before



Figure 2 After



Regards

Matahari Leisure